

BATTERY BACKUP SYSTEMS

HONBDA-BTTY-100xxx

Product Features

- NFPA Compliant
- Up to 24 hour version
- AC Input, 24 Volt DC Output
- NEMA-4 Rated BBU Enclosure
- Up to 4 Annunciators may be connected to one BBU
- Tamper Proof with Lock and Key Accessibility
- Flush Wall Mounted Annunciators
- IFC & NFPA compliance; UL2524 2nd Edition
- Country of Origin: USA
- 3-year warranty (excluding batteries)
- Common Battery Backup Systems to support BDA, Fiber DAS Master/Remote



Specification	Value
Type	Battery Backup Unit
Input	120 VAC 50/60 Hz
Size	24 x 20 x 10 in

Specifications	BTTY-100050
Storage capacity	100W / 12hs
Annunciator	AC Power Normal AC Power Failure Battery Capacity <30% Battery Charger Fail Donor Antenna Disconnection Donor Antenna Malfunction RF Emitter Fail System Component Fail
Max Load	270 W (contact Honeywell for battery duration at different loads)
Batteries	Included
BDA Annunciator	Built in, port for additional external annunciators
Weight (batteries included)	150lbs

Specifications	BTTY-100100
Storage capacity	100 W / 24 hs or 200 W / 12 hs
Annunciator	AC Power Normal AC Power Failure Battery Capacity <30% Battery Charger Fail Donor Antenna Disconnection Donor Antenna Malfunction RF Emitter Fail System Component Fail
Max Load	270 W (contact Honeywell for battery duration at different loads)

BATTERY BACKUP SYSTEMS

HONBDA-BTTY-100xxx

Batteries	Included
BDA Annunciator	Built in, port for additional external annunciators
Weight (batteries included)	210lbs

Specifications	BTTY-100050N
Storage capacity	100W / 12hs
Annunciator	AC Power Normal AC Power Failure Battery Capacity <30% Battery Charger Fail Donor Antenna Disconnection Donor Antenna Malfunction RF Emitter Fail System Component Fail
Max Load	270 W (contact Honeywell for battery duration at different loads)
Batteries	Not Included
BDA Annunciator	Built in, port for additional external annunciators
Weight	30lbs

Specifications	BTTY-100100N
Storage capacity	100 W / 24 hs or 200 W / 12 hs
Annunciator	AC Power Normal AC Power Failure Battery Capacity <30% Battery Charger Fail Donor Antenna Disconnection Donor Antenna Malfunction RF Emitter Fail System Component Fail
Max Load	270 W (contact Honeywell for battery duration at different loads)
Batteries	Not Included
BDA Annunciator	Built in, port for additional external annunciators
Weight	72lbs

Battery Models	Description
BDA-BTTY-12-1	Replacement Battery for 55AH BBU, single unit (2 batteries required)
BDA-BTTY-24-1	Replacement Battery for 100AH BBU, single unit (2 batteries required)

DOC HON-62066.02 - 12152020 - FS