NBG-12LR, NBG-12LRA, and NBG-12LRAA

Dual-Action Agent Release Stations

General

The NBG-12LR, the NBG-12LRA and the NBG-12LRAA are Agent Release Stations designed for use with NOTIFIER Fire Alarm Control Panels with releasing capabilities and RP Series Releasing Systems.

Features

- Non-coded, dual-action operation.
- Made with durable polycarbonate.
- · Optional surface backbox.

NBG-12LRA/ NBG-12LRAA INCLUDES:

- · Abort switch.
- Power-on indication.
- · Released indication.
- Manual release (dual-action).

NBG-12LR INCLUDES:

• Dual-action release only.

Applications

The NBG-12LRA and NBG-12LR are ideal for areas such as clean rooms and computer rooms where a chemical agent is used to extinguish a fire.

Product Line Information

NBG-12LRA: Agent release station with abort switch, Release LED, Normal LED.

NBG-12LRAA: Agent release station with abort switch, Release LED, and Normal LED. For ULC applications.

NBG-12LR: Dual-action agent release station.

SBA-10: Surface backbox for NBG-12LRA, metal. Dimensions 4.5" (11.43 cm) W x 8.188" (20.8 cm) L x 1.375" (3.49 cm) D.

SB-10: Surface backbox for NBG-12LR, metal. Dimensions 4.125" (10.48 cm) W x 5.5" (13.97 cm) L x 1.375" (3.49 cm) D.

SB-I/O: Surface backbox for NBG-12LR, plastic.

BG12TR: Optional trim ring for semi-flush mounting.

Agency Listings and Approvals

In some cases, certain modules may not be listed by certain approval agencies, or listing may be in progress. *Consult factory for latest listing status.*

UL/ULC Listed: S692

MEA Listed: 67-20-E

FM Approved

CSFM: 7150-0028:0199

FDNY: COA#6114 (NFS2-3030), COA#6121 (NFS2-640)

U.S. Coast Guard, Lloyd's Register, American Bureau of Shipping (ABS): For information on marine applications, see DN-60688.



NOTIFIER®

by Honeywell

Dual Action NBG-12LR



Dual Action NBG-12LR shown activated

Releasing Panels

Notifier® and FlashScan® are a registered trademark of Honeywell International Inc. Bayblend® is a registered trademark of Bayer Corp. ©2017 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.



For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118. www.notifier.com